

Low PIM Coaxial Coupler

Model No.: CC13-3527DF60

- Excellent passive intermodulation (PIM), -160dBc guaranteed.
- Wideband frequency range: 400MHz Tetra, AWS 700, CDMA 800/1900, GSM 900/1800 UMTS, LTE and WiMAX.
- 200 watts average high power rating
- Minimal RF insertion loss
- IP65 for both indoor and outdoor operations



Product Specifications:

Electrical		Mechanical	
Frequency Range (MHz)	350-960/1710-2700	Connectors	7-16 DIN-Female
VSWR	1.2	Connector Finish	Tri-metal
Return Loss	20.8 dB	Connector Inner Conduct	Silver Plating
Coupling Loss	13.0 dB	Housing Finish	Painting
Coupling Tolerance	±1.0 dB	Width	25.0 mm
Insertion Loss	0.5 dB	Length	153.8mm
Dissipative Loss	0.1dB	Height	49.3 mm
Power Rating	200 W	Weight	310.0 g
Maximum Peak Power	3 kW	Environmental	
Passive Intermodulation(PIM), 3 rd order@2*43dBm	-160dBc	Temperature Range	-40 °c to 75 °c
Input Impedance	50 Ω	Relative Humidity	0 to 100%
		Applications	Indoor & Outdoor
		IP Level	IP65

Engineering Drawings

